



Handsender Jane Q

Frequenz: 27,015 MHz/ 40,685 MHz/ 26,975 MHz/ 26,995 MHz
dbm: 10
Kanäle: 4
Batterie: 12 V alkaline
Arbeitstemperatur: -40°C - +50°C



- Geben Sie Handsender niemals in Kinderhände
- Die Handsender dürfen ausschließlich von Personen bedient werden die mit der Anlage vertraut sind und in deren Funktion eingewiesen sind
- Verwenden Sie den Handsender ausschließlich, wenn Sie das Tor einsehen können
- Das Anlernen der Handsender muss stets in der Nähe des Torantriebs vorgenommen werden. Verwenden Sie ausschließlich Originalteile
- Schützen Sie den Handsender vor Witterung wie Regen, Schnee, Sonneneinstrahlung oder auch Staub, ansonsten kann die Funktion des Senders beeinträchtigt werden
- Zum Wechseln der Batterie lösen Sie bitte die Schraube auf der Rückseite des Handsenders
- Der original Handsender und der Jane Q müssen die gleiche Frequenz haben

Programmierung:

Hinweis! Während dem gesamten Vorgang die Tasten nicht loslassen

1. Drücken und Halten Sie die Taste des Jane Handsenders, die sie programmieren möchten. Die LED leuchtet erst dauerhaft und fängt nach ca. 6-8 Sekunden an zu blinken.
2. Sobald die LED des Jane Q anfängt zu blinken, halten Sie den Jane Q und Ihren original Handsender wie auf der ersten Abbildung gezeigt aneinander, drücken und halten Sie nun auch die Taste Ihres original Handsenders, welche Sie vererben möchten. Die LED des Jane Q blinkt ein paar Sekunden weiter, leuchtet dann für ca. 2 Sekunden dauerhaft auf und geht anschließend aus. Der Kopiervorgang ist abgeschlossen und der Jane Q ist einsatzbereit.

sollte der Programmiervorgang beim ersten Versuch nicht funktioniert haben, dann wiederholen Sie den Vorgang und versuchen Sie hierbei die beiden Handsender in einer anderen Position aneinander zu halten. Siehe Abbildungen unten!



Video zur Programmierung:
finden Sie auf www.schartec.de

Warranty: 24 months – Manufacturing and technology 100% made in Italy – Patented product

Vereinfachte EU-Konformitätserklärung (CE)

The undersigned Luigino Pellattiero, legal representative of ITALFILE srl, declares that the remote control JQxxx-2/JQxxx-4, manufactured in 2011 was assembled in compliance with the following standards:

Directive 2004/10/CE – know as the Electromagnetic Compatibility Directive
Directive 2002/95/CE – known as the RoHS Directive – And therefore complies with current standards.
Luigino Pellattiero – Vincenza, 1.10.2011



Schartec
eine Marke der bau-shop-24 GmbH
Fritz-Müller-Strasse 115
73730 Esslingen



Remote Control Jane Q

Frequency: 27.015 MHz/ 40.685 MHz/ 26.975 MHz/ 26.995 MHz

dbm: 10

Channels: 4

Battery: 12 V alkaline

Working temperature: -40°C - +50°C

- Keep remotes out of reach of children.
- Remote controls may only be operated by persons who are familiar with the system and have been instructed in their function.
- Use the remote control only when you are in sight of the door / gate.
- Coding in remote controls must always be carried out within the vicinity of the door operator. Use only original parts.
- Protect remotes from rain, snow, sunlight or dust, otherwise the function of the transmitter may be impaired
- To replace the battery, unscrew the screws on the back of the remote.
- The original remote control and the pairing Jane remote must have the exact same frequency!

Programming:

1. Press and hold a button on the Jane remote control that you want to program. (do not release this button! If you release the keys after each step you will have to repeat the procedure!)
2. As soon as the LED on the Jane remote starts to flash, hold the Jane remote and your original remote as shown on the first picture.



3. Press and hold the programmed button on your original remote control.
4. When the Jane remote has received the code, the LED will remain lit for 3 seconds and then go out.
5. You may now release both buttons and operate your opener/operator.

If the transfer of the code didn't work, try holding the Jane remote and your original remote in one of the other positions as depicted above (try also holding the remotes back to back).

Programming video:

can be found at www.schartec.de/en/

Simplified EU Declaration of Conformity (CE)

Warranty: 24 months – Manufacturing and technology 100% made in Italy – Patented product
Compliance statement

The undersigned Luigino Pellattiero, legal representative of ITALFILE srl, declares that the remote control JQxxx-2/JQxxx-4, manufactured in 2011 was assembled in compliance with the following standards:

Directive 2004/10/CE – known as the Electromagnetic Compatibility Directive

Directive 2002/95/CE – known as the RoHS Directive – And therefore complies with current standards.

Luigino Pellattiero – Vincenza, 1.10.2011



Schartec
a trademark of bau-shop-24 GmbH
Fritz-Müller-Strasse 115
73730 Esslingen, Germany